



## AxiCode CCD Scanner 75x

- Interface: KB Wedge, RS-232, Wand Emulation, ADB
- Scanning Speed: 33/50/100 scans/sec (selectable)
- Weight: 138g (without cable)
- Housing: ABS and rubber
- Shock Resistance: Drops from 2.2m onto a concrete surface

### SPECIFICATIONS:

#### Interfacing Capabilities

- **Computer interface**
- |      |                                     |
|------|-------------------------------------|
| 750s | Undecoded TTL laser emulation       |
| 751s | RS232C serial                       |
| 752s | PC-AT/XT, and all compatibles, PS/2 |
| 753s | Undecode TTL wand emulation         |
| 754s | Macintosh ADB                       |

#### Reading Capabilities

- **Barcode Symbologies**

Autodiscrimination between:

1. UPC/EAN (all variations, with & without addons)
2. Interleaved 2 of 5
3. Code 39, Code 39 full ASCII
4. Codabar
5. Code 128

#### Electrical, Physical & Environmental

- **Power Consumption**
- |      |                     |                    |
|------|---------------------|--------------------|
| 750s | – 110mA, 751/2/3/4s | – 160mA at 5 Volts |
|------|---------------------|--------------------|
- **Weight**
- 138g (without cable)
- **Dimensions**
- 174.5 x 77 x 28mm (taken at widest points)
- **Operating Temperature**
- 0°C to 50°C

#### Optical

- **Light Source**
- Red LED 660nm
- **Resolution**

0.127mm (5mil)

- **Depth of Field**

15mm

- **Scan Speed**

33/50/100 scans per second (selectable)

#### Internal Firmware

- **Programming Facilities**

750/3s	None
751/2/4s	Configuration by barcode menu

- **Status Indicators**

750s	LED
751/2/3/4s	LED and audible beeper

#### Output Options (751/2s/4s only)

- Truncation of leading digits for UPC/EAN/JAN barcodes
- Prefix and Suffix options.
- Optional transmission of start/stop characters check digits and addons.

### The Range

#### Model 750s

Undecode laser emulation output. Requires an external barcode decoder.

#### Model 751s

RS232 output with built-in decoder for direct interface with serial port. Requires external power supply (5 volts DC).

#### Model 752s

Scanner with built in keyboard wedge decoder.

**Model 753s**

Undecoded wand emulation output, requires an external barcode decoder.

**Model 754s**

Decoded scanner for Macintosh ADB interface.